

CX-98A Coin Payphone

- Direct replacement for Telstra 'Gold Phone' and 'Bluephone'
 - Coins must be inserted before dialling can commence
Except programmed free calls and Emergency numbers eg; 000 and 1800.
 - Fully electronic coin Validator *Checked for alloy, thickness & diameter*
 - Accepts 10c, 20c, 50c, \$1 & \$2 coins (*New coin or token can be added*)
 - Operates on 12Khz & 50Hz pulses, 'Line Reversal' or 'Push to Talk'.
 - Operates on PTT exchange meter pulses or via programmable self-tariffing tables.
 - Can operate automatically without Telstra exchange equipment. (Limitations apply)
 - Program any numbers or prefixes as free or barred calls.
 - Coinless Calls via programmable password
 - **Programmable 'Timed' Local and 1800 Calls**
 - New Call Button (*Uses any remaining credit*)
 - Incoming calls can be timed or barred.
 - Coin safe contents recording
 - Plastic case with Metal coin safe
 - Call charges programmable
 - 16 Digit Liquid Crystal Display
 - Armored handset cord.
 - Local / STD & IDD Calls
 - Refund of unused coins.
 - Microprocessor control
 - Coin jam release button
 - Redial
 - Volume control
 - PABX compatible
 - Programming via keypad
 - Telephone Line Powered
 - Dimensions: 24 x 34 x 18 cm
 - Weight: 4kg
- Min 20mA Loop Current Required

NEW
Key Lock
Access
to Coin
Mechanism
for servicing



Optional Features

- Mounting Bracket
- Larger capacity coin safe
- Lockup banker
- Remote Management system
(Internal Modem)

Available From:



N11960

Professional Installation Recommended
Specifications Subject to Change without notice

Distributed by Telephone Technical Services Ph: 07 3286 6388 Fax: 07 3286 6399